



SCMMAN1+1/158 front view

Features

- > **PRIMARY APPLICATION:** manual changeover function across main and spare transmitter by coaxial relay control panel.
- > **HARDWARE FEATURES:** the changeover system is housed in panel rack having the dimension of 2 HE.
- > **USER-FRIENDLY FEATURES:** the front panel features many leds that indicate instant system status to the operator. It is possible to control and vary any system setting through simple buttons.
- > **EASE OF MANTENANCE:** the changeover system is assembled using modules and boards with connectors so that it is easy to remove, replace and add modules and boards.
- > **INTERFACE CONTROL:** the rear panel features all connectors that could be used to connect the equipment to other components and for piloting through remote commands and signals.

Caratteristiche

- > **PRIMARY APPLICATION:** funzionalità di scambio manuale tra trasmettitore principali e di riserva tramite il controllo di un relè coassiale.
- > **HARDWARE FEATURES:** il sistema di scambio è realizzato in pannello rack in dimensioni di 2 HE.
- > **USER-FRIENDLY FEATURES:** sul pannello frontale sono presenti una serie di indicatori led per un'immediata comprensione dello stato del sistema. Per mezzo di comodi pulsanti, è possibile controllare e modificare le impostazioni dell'intero sistema.
- > **EASE OF MANTENANCE:** il sistema di scambio è interamente assemblato con moduli e schede provvisti di connettori ad innesto, che consentono una facile rimozione, sostituzione ed aggiunta degli stessi.
- > **INTERFACE CONTROL:** sul pannello posteriore sono presenti tutti i connettori utilizzabili per il collegamento ad altri apparati e per pilotaggio tramite segnali e comandi remoti.

Telemetry & Changeover

BROADCAST
EQUIPMENT

Technical specifications

SCMMAN1+1/158

Parameter		Value
GENERALS		
Ambient working temperature		-10 °C to + 50 °C / 95% relative Humidity non condensing
INPUT		
Digital	Command Switch relay	Terminal Block
OUTPUT		
Digital	Position Relay	Terminal Block
Digital	Out of Position Relay	Terminal Block
POWER REQUIREMENTS		
AC Power Input	AC Supply Voltage	115 - 230 VAC ±15%
	Active Power Consumption	2 W
	Connector	Terminal Block (L-N-PE)
MECHANICAL DIMENSIONS		
Physical Dimensions	L x H x W	483 mm x 88 mm x 40 mm
Weight		about 0.3 kg
Cooling		Convection cooling
Acoustic Noise		0 dBA
INTERFACES		
Signalling LEDs / Synoptical	LOCAL	Yellow 5mm
	TX1 to ANT	2 x Green 5mm
	TX2 to ANT	2 x Yellow 5mm
Push Button	LOCAL ENABLE	Used for enabling change with push button
	TX1 to ANT	Used for change Relay in a POS1
	TX2 to ANT	Used for change Relay in a POS2
FUSES		
On Mains		1 Fuse 125mA - 5X20 mm

All pictures are RVR's property and they are only indicative and not binding. The pictures can be modified without notice. These are general specifications. They show typical values and are subject to change without notice.

CE 99/5/CE Revision: 04/13

telemetry
& changeover